



Rev 01.0421

850nm 10mW CW VCSEL Diode 3535 SMD Package with Collimating Lens

VC35A-850C10A-L

Description

The Lasermate VC35A-850C10A-L is an 850nm wavelength, 10mW output power, CW operating mode, Vertical Cavity Surface Emitting Laser (VCSEL) diode in surface mount (SMD) package with collimating lens designed for use in sensing applications.

Features

- 850nm VCSEL Diode with Collimating lens
- Output power: 10mW
- Single longitudinal mode
- Low wavelength drift
- Low threshold current
- · High reliability
- Collimated beam <12mrad

Applications

- Proximity sensor
- Consumer electronics
- Active optical cables
- Medical application
- Range finder sensors

Specifications

Absolute Maximum Ratings							
Parameters	Symbol	Rating	Unit	Conditions			
Case Operating Temperature	Тор	-40 to 70	°C				
Storage Temperature	Tstg	-40 to 85	°C				
Reflow Soldering Temperature	Tsol	260	°C	10 seconds			
Reverse Voltage	Vr	5	V				
Maximum Continuous Current	Imax	20	mA				
ESD Exposure (Human Body) Model	ESD	2k-4k (Class 2)	V				
ESD Exposure (Machine) Model	ESD	200-400 (Class B)	V				

Electro-Optica	al Characteristics	$(T_{op}=25^{\circ}C, CV)$	V mode)				
Parameters		Symbol	Min.	Тур.	Max.	Unit	Conditions
Optical Output	Power	Po	-	10	12	mW	I _F =11mA
Threshold Curre	ent	I _{th}	-	0.5	-	mA	
Forward Currer	nt	I _F	-	11	-	mA	
Slope Efficiency	1	η	-	1.0	-	mW/mA	
Power Conversi	ion Efficiency	PCE	-	38	-	%	
Peak Waveleng	th	λ _P	840	850	860	nm	P _o =10mW
Laser Forward \	/oltage	V _F	-	2.5	2.7	V	I _F =11mA
Series Resistano	ce	R _S	-	60	-	Ω	I _F =11mA
Beam Angle	(1/e^2)	Ө	-	12	-	mrad	I _F =11mA
	FWHM		-	-	-		I _F =11mA
Wavelength Te	mperature Drift	$\Delta \lambda_P / \Delta T$	-	0.07	-	nm/°C	I _F =11mA
Emission Area				Ф12		um	
Soldering Temp	erature				260 (10s)	°C	AIN substrate


Note: Electro-optical characteristic with a package or diffuser would require further evaluation. Values are based on limited sample size and estimated values.

Typical Characteristics

LIV Graph

12 10 8 6 -1.5 2 -20 -1.5 2 -20 -1.5 2 -20 -1.5 2 -20 -1.5 2 -20

Intensity vs. Wavelength



Notes:

1. LIV graph was measured at 25°C (left).

5

- 2. Forward voltage (V_F) measurement allowance is ±0.1V.
- 3. Peak wavelength (λ_p) measurement allowance is ± 1.5 nm.

7.5

If (mA)

10

15


12.5

4. Others measurement allowance is ±10%.

Outline Dimensions (unit: mm)


2.5

VC35A-850C10A-L (3535 SMD Package, Substrate AlN + Collimating Lens)



- 1. Package dimensions: 3.5mm x 3.5mm x 3.5mm
- 2. Collimated beam waist at optic output 3mm

SMT Reflow Soldering Curve



Note: Reflow soldering can be operated only one time. During the temperature ramp-up, no forces may be exerted on the LD which would deform or damage them. After soldering is completed, please do not process until the product temperature ramps down to room temperature.

Additional Notes

- 1. Stresses greater than those listed under "Absolute Maximum Ratings" may cause permanent damage to the device. This is a stress rating only and functional operation of the device at these or other conditions above those indicated in the operations section for expanded periods of time may affect reliability.
- 2. In its maximum rating diode laser operation could damage its performance or cause potential safety hazard such as equipment failure.
- 3. Electrostatic discharge is the main reason for laser fault of the diode. Take effective precautions against ESD. When dealing with laser diodes, use wrist strap, grounding work surface and strict antistatic technology.
- 4. Please use solder paste to cure the laser diode.
- 5. Please make sure that the heat of VCSEL diode has been completely conducted to metal shell to avoid affecting the optical power output.
- 6. This VCSEL diode can be only used in constant voltage and current.
- 7. Please do not aim the laser at people or animals.
- 8. You may observe the laser spot through an image monitoring equipment.
- Please do not touch VCSEL diode surface by naked hands or squeeze the sealant on VCSEL diode surface. It may cause wrong optical angle and distorted laser spot, and even damage the VCSEL diode.
- 10. Please use ceramic suction nozzle to absorb the VCSEL diode, so as to avoid VCSEL diode sticking to the nozzle.
- 11. Please add a 0.02s blowing action after locating the laser diode to aluminum substrate.
- 12. Specifications are subject to change without notice.



Lasermate Group, Inc. 19608 Camino De Rosa Walnut, CA 91789 USA Tel: (909)718-0999 Fax: (909)718-0998

sales@lasermate.com www.lasermate.com